

Click object to rotate

Mono











Single Monoblock 23mm LNB ,6° for 80cm dish IDLB-SINM22-MN006-8PP $\,$

Item: 5018

This monoblock LNB was designed for dual satellite reception. It can be used for the broadcast reception of any two satellites, spaced with 6° on an 80cm dish antenna, and its distribution to a single tuner Set-top box. It is optimized for High Definition transmissions, provides excellent Noise Figure performance and manufactured to the highest industry quality standards.

Main Features:

- Low phase Noise HDTV-DVBS2 compliant
- Low Noise figure of 0.2 dB
- Low Power consumption
- Very high Cross-Pole performance
- Very high Frequency stability

Technical data



Low Band Input Frequency Range $110.7 \sim 11.7 \text{ GHz}$ Low Band Output Frequency Range $950 \sim 1950 \text{ MHz}$

Low Band LO Frequency 9.75 GHz

High Band Input Frequency Range $11.7 \sim 12.75 \; \text{GHz}$ High Band Output Frequency Range $1100 \sim 2150 \; \text{MHz}$

High Band LO Frequency 10.6 GHz

Noise Figure 0.2 dB Typ. (0.7 dB Max.)

LO Initial Accuracy +/- 1.0 MHz Max.

LO Temperature Drift +/- 3.0 MHz Max.

Phase Noise (@ 10 kHz) - 90 dBc / Hz Max.

Conversion Gain $50 \sim 62 \text{ dB}$ Gain Ripple (Over 26 MHz Bandwidth) +/- 0.75 dB

Gain Variation (Over Full Band) +/- 4 dB Max. Image Rejection 40 dB Min.

1 dB Compression Point (@ Output) 0.0 dBm Min.

Control: Satellite A/B Selection DiSEqC 1.0 (Sat $A^* = \text{Hotbird } 13^\circ \text{ East}$, Sat $B = \text{ASTRA } 19.2^\circ \text{ East}$)

75 Ω

22 dB Min.

Output VSWR 2.5 : 1

Cross Polarization Isolation

Output Impedance

In-Band Spurious - 60 dBm Max.

Current Consumption 150 mA Max. @ 11 ~ 20 V


Operating Temperature $-30 \,^{\circ}\text{C} \, \sim \, +60 \,^{\circ}\text{C}$


Output Connector F-Type (Female)

Weight 270 g

Recommended Dish Size $75 \sim 85 \text{ cm (F/D} = 0.6)$

Monoblock Mounting Bracket 23 mm





For purpose of brevity, some product descriptions in this sheet remain at platform level and may not be referred to as detailed datasheets of the products. Inverto Digital Labs reserves the right to amend, omit or add products, product-lines, and / or features without notice.

