



Click object to rotate

## Pro









## Quad High-Band Circular 40mm LNB (LO10.75 GHz) IDLB-QUDR41-H1075-OPP

Item: 3315

Specifically designed for the European DTH markets, this LNB provides optimized reception capabilities for receiving circular polarized signal on the high band and enables the reception of signal from one satellite and its distribution to up-to four single tuner Set-top box (or 2 in the case of a twin- tuner STB). It is factory set for easy connectivity with any LO 10.75 Preset Set-top boxes, fully supports High Definition transmissions and provides excellent Noise Figure performance. Manufactured to the highest industry quality standards and designed to meet strict specifications, this LNB is an ideal solution for the satellite broadcast reception across Europe.

## **Main Features:**

- LO frequency 10.75 MHz
- Low phase Noise HDTV-DVBS2 compliant
- Low Noise figure
- Low Power consumption
- High Cross-Pole performance
- High Frequency stability

## **Technical data**

Investo<sup>®</sup>

I/P Frequency Range 11.7 ~ 12.75 GHz

O/P Frequency Range 950 ~ 2000 MHz

LO Frequency 10.75 GHz

LO Initial Accuracy 25 +/- 1.0 MHz

LO Temperature Drift (-30 ~ +60 ) +/- 3.0 MHz

LO Phase Noise @ 10KHz -80 dBc/Hz

Noise Figure 0.3dB Typ. (0.7dB Max.)

Conversion Gain 55 dB Min.

Gain Variation +/- 0.75 dB/27MHz

Image Rejection40 [min.]dBO/P 1 dB Compression Point0.0 [min.] dBm

Crosstalk Isolation 20 [min.]dB
Polarization Selection (Righ Hand) 10.0~14.0 V


Polarization Selection (Left Hand) 16.0~20.0 V
O/P Spurious - 60 (max.) dBc


O/P VSWR 2.5 : 1 ~

DC Power 170mA Max.@11-20V

Working Temperature  $-35 \sim +60$ Output Impedance  $75 \Omega$  (F-Type)

Weight 250 g





For purpose of brevity, some product descriptions in this sheet remain at platform level and may not be referred to as detailed datasheets of the products. Inverto Digital Labs reserves the right to amend, omit or add products, product-lines, and / or features without notice.

