



Click object to rotate

Pro

Twin Flange LNB IDLB-TWNFOO-OOPRO-OPP

Item: 3214







Specifically designed for the European DTH markets, this LNB provides optimized reception capabilities. It enables the reception of signal from one satellite and its distribution to up-to two single tuner Set-top box (or 1 in the case of a twin- tuner STB). It is ready for High Definition transmissions and provides excellent Noise Figure performance. Manufactured to the highest industry quality standards and designed to meet strict specifications, this LNB is an ideal solution for the satellite broadcast reception across Europe.

Main Features:

- Low phase Noise HDTV-DVBS2 compliant
- Low Noise figure
- Low Power consumption
- High Cross-Pole performance
- High Frequency stability



Technical data

Crosstalk Isolation

Invector.

Low Band I/P Frequency Range $10.7 \sim 11.7 \text{ GHz}$ O/P Frequency Range $950 \sim 1950 \text{ MHz}$

LO Frequency 9.75 GHz

High Band I/P Frequency Range $11.7 \sim 12.75 \; \text{GHz}$ O/P Frequency Range $1100 \sim 2150 \; \text{MHz}$

LO Frequency 10.6 GHz
Noise Figure 0.2 dB

LO Initial Accuracy +/- 1.0 MHz
LO Temperature Drift +/- 3.0 MHz
LO Phase Noise @ 10K Hz -80 dBc / Hz
Conversion Gain 55 dB Min.
Gain Variation +/-8 dB
Image Rejection 40 [min.]dB
O/P 1 dB Compression Point 0.0 [min.] dBm


Control Signals Ca [V] $10.0 \sim 14.0 \text{ V}$ Control Signals Cb [H] $16.0 \sim 20.0 \text{ V}$ Control Signals Cc 22 +/- 4 KHz O/P Supurious -60 [max.] dBc

O/P VSWR 2.5 : 1 \sim Radiated Interference -50 dBm

DC Power 120mA Max.@11-20V

Working Temperature $-30 \sim +60$ Output Impedance 75Ω (F-Type)

Weight 180 g



20 [min.]dB

For purpose of brevity, some product descriptions in this sheet remain at platform level and may not be referred to as detailed datasheets of the products. Inverto Digital Labs reserves the right to amend, omit or add products, product-lines, and / or features without notice.

