

Click object to rotate

## Mono











Twin Monoblock 23mm LNB ,4.3° for 60cm dish IDLB-TWNM22-DUO43-6PP 6°3°

Item: 3529

This Monoblock LNB was specifically designed for the Netherlands for the reception of ASTRA 19.2° East and 23.5° East and the independent distribution of their signal to up to 2 single tuner Set-top boxes (or 1 in the case of a double-tuner STB). It can be used for satellite broadcast reception of any two satellites spaced with 4.3° degrees on an 60cm dish antenna. It is optimized for High Definition transmissions, provides excellent Noise Figure performance and manufactured to the highest industry quality standards.

## **Main Features:**

- Two outputs
- Low phase noise HDTV/DVB-S2 compliant
- Low Power consumption
- Very high Cross-Polar and Cross-Satellite performance

## **Technical data**



ILow Band Input Frequency Range $10.7 \sim 11.7 \text{ GHz}$ Low Band Output Frequency Range $950 \sim 1950 \text{ MHz}$ 

Low Band LO Frequency 9.75 GHz

High Band Input Frequency Range  $11.7 \sim 12.75 \; \text{GHz}$ High Band Output Frequency Range  $1100 \sim 2150 \; \text{MHz}$ 

High Band LO Frequency 10.6 GHz

Noise Figure 0.2 dB Typ. (0.7 dB Max.)

LO Initial Accuracy +/- 1.0 MHz Max.

LO Temperature Drift +/- 3.0 MHz Max.

Phase Noise (@ 10 kHz) - 90 dBc / Hz Max.

Conversion Gain 50 ~ 60 dB Min.

Gain Ripple (Over 26 MHz Bandwidth) +/- 0.75 dB

Gain Variation (Over Full Band) +/- 4 dB Max.

Image Rejection 40 dB Min.

1 dB Compression Point (@ Output) 0.0 dBm Min.

Control: Satellite A/B Selection "DiSEqC 1.0 (Sat  $A^* = ASTRA 19.2^\circ$  East, Sat  $B = ASTRA 23.5^\circ$  East)"

Cross Polarization Isolation 22 dB Min.

Output VSWR 2.5 : 1

In-Band Spurious - 60 dBm Max.

Current Consumption 200 mA Max. @ 11 ~ 20 V

Operating Temperature - 30 °C ~ + 60 °C


Output Impedance  $75 \Omega$ 


Output Connector F-Type (Female)

Weight 495 g

Recommended Dish Size  $55 \sim 65 \text{ cm (F/D} = 0.6)$ 

Monoblock Mounting Bracket 23 mm





For purpose of brevity, some product descriptions in this sheet remain at platform level and may not be referred to as detailed datasheets of the products. Inverto Digital Labs reserves the right to amend, omit or add products, product-lines, and / or features without notice.

